

## RN221N

### Active barrier with optional HART® diagnosis

Active barrier with power supply for safe separation of 4...20 mA current circuits



from **THB6,547.00**

Price as of 25.05.2022

More information and current pricing:

[www.th.endress.com/RN221N](http://www.th.endress.com/RN221N)

#### Benefits:

- Wide range power supply, flexible power source
- Compact side by side DIN rail housing
- International Ex approvals; marine approval
- Bidirectional HART® transmission. Communication sockets for HART® sensor setting up. Evaluation of status information from connected transmitter with HART® protocol.
- Primary or secondary master operating mode, automatic selection
- Sensor monitoring with early-warning system
- Manual or automatic reset of the relay contact

#### Specs at a glance

- **Input** 1 x analog 4...20 mA
- **Output** 1 x analog 4...20 mA

**Field of application:** The active barrier RN221N supplies e.g. a transmitter with power, if required also in the Ex-area, and then transmits the galvanically isolated signal. With the optionally available HART® monitoring the status of the transmitter is monitored. If an error arises a relay at the RN221N sends an alarm. The relay has to be actively set back. Thus even just briefly occurring errors can be easily located.

#### Features and specifications

Acquisition / Evaluation

**Measuring principle**

Power supply

---

**Acquisition / Evaluation****Function**

Active barrier with power supply for safe separation of 4...20 mA current circuit

---

**Certification**

ATEX II(1)GD(Ex ia)IIC  
FM USA IS  
FM USA NI  
CSA IS  
CSA NI  
IECEX Ex ia  
TIIS Ex ia  
GOST Ex i  
Marine approval  
SIL  
Hygenic WHG

---

**Input**

1 x analog 4...20 mA

---

**Output**

1 x analog 4...20 mA

---

**Relay output**

1 x no contact

---

**Auxiliary power supply / Loop power supply**

20...250 V DC/AC

---

**Dimensions (wxhxd)**

22.5 x 110 x 112 mm  
(0.89" x 4.33" x 4.41")

---

**Operation**

HART

---

---

**Power supplies & barrier****Measuring principle**

Active barrier

---

**Measuring principle**

Power supply

---

**Function**

Active barrier with power supply for safe separation of 4...20 mA current circuit

---

**Loop power supply**

20...250 V DC/AC

---

**Auxiliary power supply / Loop power supply**

20...250 V DC/AC

---

**Input**

1 x analog 4...20 mA

---

**Output**

1 x analog 4...20 mA

---

**Certificates**

ATEX (Ex ia)

FM AIS

CSA (Ex ia)

IECEX (Ex ia)

NEPSI (Ex ia)

JPN (Ex ia)

Non-hazardous area + EAC marking

EAC (Ex ia)

---

**Operation**

HART

---

More information [www.th.endress.com/RN221N](http://www.th.endress.com/RN221N)